

## Quasiparticle Relaxation of Superconducting Qubits in the Presence of Flux

G. Catelani,<sup>1</sup> J. Koch,<sup>2</sup> L. Frunzio,<sup>1</sup> R. J. Schoelkopf,<sup>1</sup> M. H. Devoret,<sup>1</sup> and L. I. Glazman<sup>1</sup>

<sup>1</sup>*Departments of Physics and Applied Physics, Yale University, New Haven, Connecticut 06520, USA*

<sup>2</sup>*Department of Physics and Astronomy, Northwestern University, Evanston, Illinois 60208, USA*

(Received 28 September 2010; published 16 February 2011)

Quasiparticle tunneling across a Josephson junction sets a limit for the lifetime of a superconducting qubit state. We develop a general theory of the corresponding decay rate in a qubit controlled by a magnetic flux. The flux affects quasiparticles tunneling amplitudes, thus making the decay rate flux-dependent. The theory is applicable for an arbitrary quasiparticle distribution. It provides estimates for the rates in practically important quantum circuits and also offers a new way of measuring the phase-dependent admittance of a Josephson junction.

DOI: 10.1103/PhysRevLett.106.077002

PACS numbers: 74.50.+r, 85.25.Cp

Long coherence times of superconducting qubits rely on the decoupling of the order parameter quantum oscillations from other low-energy degrees of freedom. Quasiparticles provide an intrinsic set of states capable of exchanging energy with the qubit degree of freedom. In equilibrium, quasiparticle populations should get completely depleted at low temperatures, rendering the corresponding qubit relaxation channel ineffective. In practice, however, some nonequilibrium quasiparticles are observed [1,2]. The question whether the relaxation driven by quasiparticles is comparable to the extrinsic mechanisms of qubit relaxation has remained open.

The theory of quasiparticle relaxation was addressed in [3] for a charge qubit, whose computational space consists of two values of charge of the same parity (even or odd) stored in a Cooper pair box. The elementary process of relaxation essentially amounts to the well-studied quasiparticle poisoning [4,5]: a quasiparticle entering the Cooper pair box changes the parity of the state. Later, the theory [3] was modified to estimate the effect of quasiparticles in a “transmon” device [6], where the dominant energy scale comes from the Josephson inductance. Further consideration of the relaxation induced by quasiparticles in superconducting qubits was developed in Ref. [2]. The properties of qubits such as the phase and flux qubits [7], the transmon, and the fluxonium [8] can be tuned by threading a magnetic flux through the device.

Here, we predict that the relaxation rates induced by quasiparticle tunneling depend on the magnetic flux threading the qubit. The theory we develop allows for any quasiparticle distribution and any magnitude of quantum fluctuations of the phase of the order parameter; thus, it provides relaxation rates for the entire spectrum of superconducting qubits. We also show that a spectroscopic measurement on a device designed to have small phase fluctuations may enable one to measure the enigmatic phase dependence of the Josephson junction admittance [9].

We consider the system consisting of a Josephson junction closed by an inductive loop. The Hamiltonian  $\hat{H}$

governing the low-energy dynamics of the system can be divided into three parts

$$\hat{H} = \hat{H}_\varphi + \hat{H}_{\text{qp}} + \hat{H}_T. \quad (1)$$

The first term takes the form of the inductively shunted Josephson junction

$$\hat{H}_\varphi = 4E_C(\hat{N} - n_g)^2 - E_J \cos \hat{\varphi} + \frac{1}{2}E_L \left( \hat{\varphi} - 2\pi \frac{\Phi_e}{\Phi_0} \right)^2, \quad (2)$$

where  $\hat{N} = -id/d\varphi$  is the number operator of Cooper pairs passed across the junction,  $n_g$  is the dimensionless gate voltage,  $\Phi_e$  is the external flux threading the loop, and  $\Phi_0 = h/2e$  is the flux quantum. With appropriate choices for the parameters characterizing the qubit—charging energy  $E_C$ , Josephson energy  $E_J$ , and inductive energy  $E_L$ —and of the biases  $n_g$  and  $\Phi_e$ , Eq. (2) can describe a single-junction qubit and also a multijunction one, so long as an array of junctions with energies  $E_j^a \gg E_J$  is treated as an effective inductance [10].

The quasiparticle term  $\hat{H}_{\text{qp}}$  is the sum of the BCS quasiparticle Hamiltonians for the left and right leads

$$\hat{H}_{\text{qp}} = \sum_{j=L,R} \hat{H}_{\text{qp}}^j, \quad \hat{H}_{\text{qp}}^j = \sum_{n,\sigma} \epsilon_n^j \hat{\alpha}_{n\sigma}^{j\dagger} \hat{\alpha}_{n\sigma}^j. \quad (3)$$

Here  $\hat{\alpha}_{n\sigma}^j$  ( $\hat{\alpha}_{n\sigma}^{j\dagger}$ ) is the quasiparticle annihilation (creation) operator,  $\sigma = \uparrow, \downarrow$  accounts for spin, and the quasiparticle energies are  $\epsilon_n^j = \sqrt{(\xi_n^j)^2 + (\Delta^j)^2}$ , with  $\xi_n^j$  and  $\Delta^j$  being the single-particle energy level  $n$  in the normal state of lead  $j$ , and the gap parameter in that lead, respectively. Finally,  $\hat{H}_T$  describes quasiparticle tunneling across the junction,

$$\hat{H}_T = t \sum_{n,m,\sigma} (e^{i(\hat{\varphi}/2)} u_n^L u_m^R - e^{-i(\hat{\varphi}/2)} v_m^R v_n^L) \hat{\alpha}_{n\sigma}^{L\dagger} \hat{\alpha}_{m\sigma}^R + \text{H.c.} \quad (4)$$

The tunneling amplitude  $t \ll 1$  is determined by the junction conductance  $g = 4\pi e^2 \nu^L \nu^R t^2 / \hbar$ ; we assume identical

densities of states per spin direction in the leads,  $\nu^L = \nu^R = \nu_0$ . The Bogoliubov amplitudes  $u_n^j, v_n^j$  can be taken real, since Eq. (4) already accounts explicitly for the phases of the order parameters in the leads via the gauge-invariant phase difference [9] in the exponentials. Accounting for Josephson effect and quasiparticles dynamics by Eqs. (2) and (4) is possible as long as qubit and quasiparticles energies (measured from  $\Delta$ ) are small compared to  $\Delta$  [3]. In this low-energy limit, we may approximate  $u_m^j \approx v_n^j \approx 1/\sqrt{2}$ . Then the operators  $e^{\pm i\hat{\phi}/2}$  in Eq. (4) which describe transfer of charge  $\pm e$  across the junction, combine to  $\sin(\hat{\phi}/2)$ . The superposition of the tunneling amplitudes containing  $e^{i\hat{\phi}/2}$  and  $e^{-i\hat{\phi}/2}$  is a manifestation of interference between tunneling of particle- and holelike excitations, possible in the presence of the Cooper pair condensate. We stress that the phase  $\hat{\phi}$  is an operator subject to quantum fluctuations, as determined by  $\hat{H}_\varphi$ , not an externally controlled parameter as in the ‘‘classical’’ Josephson junction [9]. Moreover, the nonlinear phase-quasiparticle coupling is in stark contrast with the linear coupling between phase and the electromagnetic environment.

In general, the qubit Hamiltonian in Eq. (2) has a discrete low-energy spectrum. The tunneling term, Eq. (4), couples the qubit to the quasiparticles; therefore, a transition between initial,  $|i\rangle$ , and final,  $|f\rangle$ , qubit states becomes possible when a quasiparticle is excited during a tunneling event. The transition rate  $\Gamma_{i \rightarrow f}$  can be calculated using Fermi’s golden rule,

$$\Gamma_{i \rightarrow f} = \frac{2\pi}{\hbar} \sum_{\{\lambda\}_{\text{qp}}} \langle\langle |f\rangle, \{\lambda\}_{\text{qp}} | \hat{H}_T | i\rangle, \{\eta\}_{\text{qp}} \rangle \delta(E_{\lambda, \text{qp}} - E_{\eta, \text{qp}} - \hbar\omega_{if}) \rangle\rangle_{\text{qp}}, \quad (5)$$

where  $\hbar\omega_{if}$  is the energy difference between the qubit states,  $E_{\eta, \text{qp}}$  and  $E_{\lambda, \text{qp}}$  are the total energies of the quasiparticles in their respective initial  $\{\eta\}_{\text{qp}}$  and final  $\{\lambda\}_{\text{qp}}$  states; double angular brackets  $\langle\langle \dots \rangle\rangle_{\text{qp}}$  denote averaging over the initial quasiparticle states whose occupation is determined by the distribution functions  $f^j(\xi_n^j) = \langle\langle \hat{\alpha}_{n\uparrow}^{j\dagger} \hat{\alpha}_{n\uparrow}^j \rangle\rangle_{\text{qp}} = \langle\langle \hat{\alpha}_{n\downarrow}^{j\dagger} \hat{\alpha}_{n\downarrow}^j \rangle\rangle_{\text{qp}}$  ( $j = L, R$ ) assumed to be independent of spin. In terms of the matrix elements of the operator  $\sin(\hat{\phi}/2)$  we find

$$\Gamma_{i \rightarrow f} = \left| \left\langle f \left| \sin \frac{\hat{\phi}}{2} \right| i \right\rangle \right|^2 S_{\text{qp}}(\omega_{if}). \quad (6)$$

In deriving Eq. (6) we have made a simplifying assumption of equal gaps,  $\Delta_L = \Delta_R = \Delta$ . More importantly, we concentrate on the case of low-lying excitations, assuming the characteristic energy  $\delta E$  of the quasiparticles (determined by the distribution functions; in thermal equilibrium,  $\delta E = k_B T$ ) and the energy of the qubit transition  $\hbar\omega_{if}$  are small,  $\hbar\omega_{if}, \delta E \ll 2\Delta$ . That enables us to factorize the transition rate  $\Gamma_{i \rightarrow f}$  into a product of terms which depend separately on the qubit dynamics and quasiparticle

kinetics. The latter determines the normalized quasiparticle current spectral density  $S_{\text{qp}}$ ,

$$S_{\text{qp}}(\omega) = \frac{8E_J}{\pi\hbar} \int_0^\infty dx \frac{1}{\sqrt{x}\sqrt{x + \hbar\omega/\Delta}} [f_E^L((1+x)\Delta) \times (1 - f_E^R((1+x)\Delta + \hbar\omega)) + (L \leftrightarrow R)], \quad (7)$$

where  $\omega > 0$  and we used the relation  $E_J = g\Delta/8g_K$ ;  $g_K = e^2/h$  is the conductance quantum. The integrand in  $S_{\text{qp}}$  equals, up to a factor, the rate of transitions of a quasiparticle between the initial and final states, properly weighted with their occupation probabilities (their energies are  $(1+x)\Delta$  and  $(1+x)\Delta + \hbar\omega$ , respectively). These probabilities are expressed in terms of the quasiparticle energy distribution functions,  $f_E^j(\epsilon) = (f^j(\xi) + f^j(-\xi))/2$ , with  $\epsilon = \sqrt{\xi^2 + \Delta^2}$  and  $j = L, R$ .

We notice that  $S_{\text{qp}}$  is related to the real part of the quasiparticle contribution to the classical [9] Josephson junction admittance at zero phase difference,

$$S_{\text{qp}}(\omega) - S_{\text{qp}}(-\omega) = \omega \text{Re} Y_{\text{qp}}(\omega)/\pi g_K, \quad (8)$$

at arbitrary ratio  $\hbar\omega/\delta E$  and for any quasiparticle distribution function. In the rest of this Letter we consider the ‘‘high-frequency’’ limit [12]  $\hbar\omega/\delta E \gg 1$  (but still  $\hbar\omega \ll 2\Delta$ ), and equal populations on the two sides of the junction,  $f^L = f^R$ . Then we can simplify Eq. (8),

$$S_{\text{qp}}(\omega) = \omega \text{Re} Y_{\text{qp}}(\omega)/\pi g_K, \quad \omega > 0, \quad (9)$$

and express  $\text{Re} Y_{\text{qp}}$  in terms of the quasiparticle density

$$n_{\text{qp}} = 2\sqrt{2}\nu_0\Delta \int_0^\infty \frac{dx}{\sqrt{x}} f_E((1+x)\Delta) \quad (10)$$

(written using the same approximations as above) as

$$\text{Re} Y_{\text{qp}}(\omega) = \frac{1}{2} x_{\text{qp}} g \left( \frac{2\Delta}{\hbar\omega} \right)^{3/2}, \quad x_{\text{qp}} = \frac{n_{\text{qp}}}{2\nu_0\Delta}. \quad (11)$$

Here,  $x_{\text{qp}}$  is the quasiparticle density normalized by the density of Cooper pairs; in thermal equilibrium,  $x_{\text{qp}} = \sqrt{2\pi k_B T/\Delta} e^{-\Delta/k_B T}$ . Under the above stated assumptions, Eq. (11) applies to an otherwise arbitrary distribution function, and hence to nonequilibrium conditions.

The dependence of the relaxation rate, Eq. (6), on quasiparticle density via Eq. (9) and (11) is analogous to the dependence on  $n_{\text{qp}}$  of the Mattis-Bardeen [13] dissipative ac response of a ‘‘dirty’’ superconductor, generalized to nonequilibrium distributions [14] (this connection was noticed in [2]). In both cases dissipation is caused by transitions between microscopic quasiparticle levels occurring without momentum conservation. In our case, these transitions are due to the coupling to the qubit degree of freedom, characterized by the matrix element  $\langle f | \sin(\hat{\phi}/2) | i \rangle$  in Eq. (6) which is sensitive to flux [15].

We stress that Eq. (6) holds for any single-junction qubit, its properties being encoded in the wave functions  $|i\rangle, |f\rangle$  entering the matrix element. For a qubit comprising

multiple junctions  $\hat{H}_T$  in Eq. (4) and hence Eq. (6) are given by a sum over junctions, with  $\hat{\varphi}$  being replaced by the phase difference across each junction. In a multijunction qubit, the states  $|i\rangle$  and  $|f\rangle$  depend on all the phase differences (up to the constraint set by fluxoid quantization [11]).

We focus first on the case of a weakly anharmonic system, which already reveals a nontrivial flux dependence of relaxation. Its low-lying states, as the example of the transmon shows [6], can be used as qubit states. We assume  $E_L \neq 0$  to eliminate  $n_g$  by a gauge transformation [16]. In the transmon  $E_L = 0$ , but the  $n_g$ -dependent corrections are exponentially small [6]; hence, the results below can be applied to a single-junction transmon by setting  $\varphi_0 = 0$ . In the limit  $E_C \ll E_J, E_L$ , Eq. (2) describes an ideal  $LC$  circuit with a junction in parallel. The phase across the junction is determined, up to small fluctuations, by the external flux. Minimization of the potential energy in Eq. (2), shows that the phase  $\varphi_0$  at the minimum satisfies

$$E_J \sin \varphi_0 + E_L(\varphi_0 - 2\pi\Phi_e/\Phi_0) = 0. \quad (12)$$

Near this minimum, the system behaves as a weakly anharmonic oscillator. Anharmonicity and quality factor  $Q$  determine the operability of the system as a qubit [7]. In the present case, the operability condition can be written as  $Q/n_w \gg 1$ , where  $n_w$  is the number of levels in the anharmonic well. For large  $Q$  the system can therefore be operated as a qubit despite its weak anharmonicity. To the leading order in  $E_C/(E_L + E_J \cos \varphi_0)$  [17] and for low-lying levels  $n \ll n_w$ , we can neglect anharmonic corrections when evaluating the matrix element in Eq. (6) [18]. Its value for transitions between two neighboring levels is approximated as

$$\left| \langle n-1 \left| \sin \frac{\hat{\varphi}}{2} \right| n \rangle \right|^2 = n \frac{E_C}{\hbar \omega_{10}} \frac{1 + \cos \varphi_0}{2}, \quad (13)$$

with  $\omega_{10} = \sqrt{8E_C(E_L + E_J \cos \varphi_0)}/\hbar$ . In deriving Eq. (13), we replaced  $\sin(\hat{\varphi}/2)$  by its linear expansion, which sets the limit on the excitation level,  $n \ll \hbar \omega_{10}/E_C$ . For higher  $n$  quantum fluctuations of phase are significant and transitions between distant levels proliferate, due to the nonlinearity of the operator  $\sin(\hat{\varphi}/2)$ .

Concentrating on  $n \ll \hbar \omega_{10}/E_C$ , we use  $E_C = e^2/2C$  and Eqs. (6), (9), and (13) to find

$$\Gamma_{n \rightarrow n-1} = \frac{n}{C} \text{Re} Y_{\text{qp}}(\omega_{10}) \frac{1 + \cos \varphi_0}{2}. \quad (14)$$

For the transition between the two lowest states ( $n = 1 \rightarrow 0$ ) and in the absence of magnetic flux ( $\varphi_0 = 0$ ), Eq. (14) reduces to the expression for the rate of Ref. [2].

Using now Eq. (14) with  $n = 1$ , we find the inverse of the transition  $Q$  factor at arbitrary  $\varphi_0$ ,

$$\frac{1}{Q_{10}} = \frac{\Gamma_{1 \rightarrow 0}}{\omega_{10}} = \frac{1}{\pi g_K} \text{Re} Y_{\text{qp}}(\omega_{10}) \frac{E_C}{\hbar \omega_{10}} \frac{1 + \cos \varphi_0}{2}. \quad (15)$$

Note that  $\varphi_0$  and hence the transition frequency  $\omega_{10}$  depend on the external flux  $\Phi_e$ , see Eq. (12). We stress that

the flux dependence presented here is specific to the single-junction case; results for multiple-junction qubits will be presented elsewhere. In the limit  $E_J \gg E_L$ , the flux dependence can be neglected and the last factor on the right-hand side of Eq. (15) reduces to  $\approx 1$ . Qubit  $Q$  factors measured at temperatures  $\sim 20$  mK are in the range  $10^4$ – $10^5$  [19]. Using typical parameters for Al-based qubits ( $\Delta \sim 2 \times 10^{-4}$  eV,  $\omega_{10}/2\pi \sim 1$ – $10$  GHz) we find that to reproduce the experimental  $Q$  factors with Eq. (15) and a thermal equilibriumlike quasiparticle density, we must assume an effective quasiparticle temperature an order of magnitude larger than the base temperature. This points either to the quasiparticles being in a nonequilibrium state whose origin is at present unclear, or to the prevalence of extrinsic relaxation mechanisms.

Beside causing dissipation, quasiparticle tunneling leads to a shift in the resonant frequency of the circuit. In the regime under consideration, the resonant frequency is the zero of the total admittance  $Y(\omega)$  which for the parallel elements representing the qubit is  $Y = Y_C + Y_L + Y_J$ , with  $Y_C = i\omega C$ ,  $Y_L = 1/i\omega L$ , and the junction admittance  $Y_J$  being the sum [9] of a purely inductive Josephson term and a quasiparticle term,

$$Y_J(\omega, \varphi) = \frac{(1 - 2x_{\text{qp}}^A)}{iL_J \omega} \cos \varphi + Y_{\text{qp}}(\omega) \frac{1 + \cos \varphi}{2}. \quad (16)$$

Here,  $L_J = \hbar/\pi g \Delta$  is the conventionally defined Josephson junction inductance,  $x_{\text{qp}}^A = f_E(\Delta)$  has the meaning of the population of Andreev levels [20] ( $x_{\text{qp}}^A = e^{-\Delta/k_B T}$  in thermal equilibrium), and

$$Y_{\text{qp}}(\omega) = -\frac{2}{iL_J \omega} \left[ \frac{x_{\text{qp}}}{\pi} \sqrt{\frac{\Delta}{i\hbar \omega}} - x_{\text{qp}}^A \right] \quad (17)$$

is the quasiparticle admittance at zero phase difference in the high-frequency limit [its real part agrees with Eq. (11)]. Both free ( $x_{\text{qp}}$ ) and bound ( $x_{\text{qp}}^A$ ) quasiparticles affect  $Y_J$ . The frequency shift they cause, measured from the frequency in the absence of quasiparticles, is found by solving  $Y_C + Y_L + Y_J = 0$  at linear order in  $x_{\text{qp}}, x_{\text{qp}}^A$ :

$$\delta \omega = \frac{i}{2C} Y_{\text{qp}}(\omega_{10}) \frac{1 + \cos \varphi_0}{2} - \frac{\pi g \Delta}{C \hbar \omega_{10}} x_{\text{qp}}^A \cos \varphi_0. \quad (18)$$

The imaginary part  $\delta \omega''$  of frequency shift reproduces—when Eq. (17) for the admittance is used—half the dissipation rate  $\Gamma_{1 \rightarrow 0}$  calculated above, while the real part  $\delta \omega'$  in the high-frequency limit equals

$$\delta \omega' = \frac{1}{2} \frac{\omega_p^2}{\omega_{10}} \left[ x_{\text{qp}}^A (1 - \cos \varphi_0) - \frac{x_{\text{qp}}}{2\pi} \sqrt{\frac{2\Delta}{\hbar \omega_{10}}} (1 + \cos \varphi_0) \right], \quad (19)$$

where  $\omega_p = \sqrt{8E_J E_C}/\hbar$  is the junction plasma frequency. The relation Eq. (18) for  $\delta \omega$  in the weakly anharmonic regime opens new ways to study experimentally the effect of quasiparticles on the Josephson junction admittance. It may elucidate the phase dependence of its dissipative

part, where experimental data are still controversial. Measuring  $\delta\omega''$  along with  $\delta\omega'$ , Eqs. (18) and (19), may also shed light on the nature of nonequilibrium quasiparticle distributions: unlike the dissipative part,  $\delta\omega'$  depends on both  $x_{\text{qp}}^A$  and  $x_{\text{qp}}$ . Experimental efforts to verify the flux and quasiparticle density dependence of  $\delta\omega$  are in progress in our group and elsewhere [21].

The nonlinear interaction between phase and quasiparticles enables transitions between distant levels even in a harmonic-oscillator potential. At  $E_C/\hbar\omega_{10} \ll 1$  these transitions are suppressed by the smallness of quantum fluctuations. For example,  $\Gamma_{2\rightarrow 0}$  appears only in the second order in fluctuations of  $\hat{\varphi}$  around  $\varphi_0$ ,

$$\Gamma_{2\rightarrow 0} = \frac{2\omega_{10}}{\pi} \frac{1}{g_K} \text{Re}Y_{\text{qp}}(2\omega_{10}) \left( \frac{E_C}{\hbar\omega_{10}} \right)^2 \frac{1 - \cos\varphi_0}{4}. \quad (20)$$

Here,  $\text{Re}Y_{\text{qp}}$  is given by Eq. (11). Notice the difference in the  $\varphi_0$  dependence between Eqs. (14) and (20).

The effect of nonlinear in  $\hat{\varphi}$  coupling of the qubit degree of freedom to quasiparticles is striking for a system with  $E_J > E_L$  biased near half the flux quantum [22]. Then the potential in Eq. (2) has a pronounced double-well shape and the qubit states  $|0\rangle$  and  $|1\rangle$  are the lowest tunnel-split eigenstates [7]. The rate  $\Gamma_{1\rightarrow 0}$  in a single-junction qubit vanishes at  $\Phi_e = \Phi_0/2$  due to the destructive interference: at that point, the potential in Eq. (2) and function  $\sin\varphi/2$  in Eq. (6) are symmetric around  $\varphi = \pi$ , while the qubit states  $|0\rangle$ ,  $|1\rangle$  are symmetric and antisymmetric, respectively. (The symmetry and its consequences are missed if the  $\sin\hat{\varphi}/2$  interaction is replaced with the linear phase-quasiparticle coupling accepted in the environmental approach.) To evaluate  $\Gamma_{1\rightarrow 0}$  at finite  $\Phi_e - \Phi_0/2$  for a qubit governed by Eq. (2)—i.e., a single junction connected to an (effective) inductor—we assume tunnel splitting [6,16]

$$\epsilon_0 = 4 \left( \frac{2}{\pi} \right)^{1/2} \hbar\omega_p \left( \frac{8E_J}{E_C} \right)^{1/4} e^{-\sqrt{8E_J/E_C}} \quad (21)$$

to be small compared to inductive and plasma energies,  $\hbar\omega_p \gg E_L \gg \epsilon_0$ . Evaluating the matrix element in Eq. (6) in a tight-binding approximation and using Eq. (9), we arrive at

$$\Gamma_{1\rightarrow 0} = \frac{\omega_{10}}{\pi g_K} \text{Re}Y_{\text{qp}}(\omega_{10}) \left( \frac{\epsilon_0}{4\pi E_J} \right)^2 \left[ 1 - \frac{\epsilon_0^2}{(\hbar\omega_{10})^2} \right], \quad (22)$$

where the transition frequency is related to the flux by  $\omega_{10} = \sqrt{\epsilon_0^2 + [(2\pi)^2 E_L (\Phi_e/\Phi_0 - 1/2)]^2/\hbar}$  and  $\text{Re}Y_{\text{qp}}$  is given in Eq. (11).

In summary, we have presented a general approach to study the quasiparticle relaxation mechanism of superconducting qubits. It enables us to determine how the qubit decay rate depends on the magnetic flux used to tune the system properties. The method is applicable to any superconducting qubit and arbitrary quasiparticle population.

For small phase fluctuations and transitions between neighboring levels, the decay rate can be expressed in terms of the real part of the classical [9] junction admittance, see Eq. (14), while the imaginary part of the admittance determines the shift in the qubit frequency [Eq. (19)]. This limit is applicable, e.g., to a single-junction transmon. Decay rate and frequency shift have distinct dependencies on flux and quasiparticle distribution, so comparing the two quantities may give information on the (possibly) nonequilibrium state of quasiparticles.

This work was supported by IARPA (ARO Contract No. W911NF-09-1-0369), NSF (DMR Grant No. 0906498), and Yale University. L.F. acknowledges partial support from CNR-Istituto di Cibernetica.

- 
- [1] J. A. Schreier *et al.*, *Phys. Rev. B* **77**, 180502(R) (2008).
  - [2] J. M. Martinis, M. Ansmann, and J. Aumentado, *Phys. Rev. Lett.* **103**, 097002 (2009).
  - [3] R. M. Lutchyn, L. I. Glazman, and A. I. Larkin, *Phys. Rev. B* **72**, 014517 (2005).
  - [4] K. A. Matveev *et al.*, *Phys. Rev. Lett.* **70**, 2940 (1993).
  - [5] P. Joyez *et al.*, *Phys. Rev. Lett.* **72**, 2458 (1994).
  - [6] J. Koch *et al.*, *Phys. Rev. A* **76**, 042319 (2007).
  - [7] M. H. Devoret and J. M. Martinis, *Quant. Info. Proc.* **3**, 163 (2004).
  - [8] V. E. Manucharyan *et al.*, *Science* **326**, 113 (2009).
  - [9] A. Barone and G. Paternò, *Physics and Applications of the Josephson Effect* (Wiley, New York, 1982).
  - [10] This treatment is applicable to arrays of  $N \gg 1$  junctions with small phase fluctuations [8]. The Hamiltonian of a qubit with few junctions of similar parameters is the sum of each junction's charging and Josephson energies [11]; see the paragraph preceding that containing Eq. (12).
  - [11] T. P. Orlando *et al.*, *Phys. Rev. B* **60**, 15398 (1999).
  - [12] Therefore, everywhere below we dispense with the probability of "upward transitions" for which  $\omega_{if} < 0$ .
  - [13] D. C. Mattis and J. Bardeen, *Phys. Rev.* **111**, 412 (1958).
  - [14] G. Catelani, L. I. Glazman, and K. E. Nagaev, *Phys. Rev. B* **82**, 134502 (2010).
  - [15] The flux dependence was not considered in Ref. [2]—there, the perturbation driving the quasiparticle transitions was assumed to be independent of flux.
  - [16] J. Koch *et al.*, *Phys. Rev. Lett.* **103**, 217004 (2009).
  - [17] At  $E_J > E_L$  this ratio is not small and the potential has multiple minima at some values of flux. Here we assume nondegenerate wells—see the discussion leading to Eq. (22) for the nearly symmetric case.
  - [18] The flux-biased phase qubit of R. W. Simmonds *et al.*, *Phys. Rev. Lett.* **93**, 077003 (2004), with  $n_w \sim 4$  can be analyzed using Eq. (13) as a first approximation.
  - [19] A. A. Houck *et al.*, *Phys. Rev. Lett.* **101**, 080502 (2008).
  - [20] C. W. J. Beenakker, in *Transport Phenomena in Mesoscopic Systems*, edited by H. Fukuyama and T. Ando (Springer, Berlin, 1992).
  - [21] M. Lenander *et al.*, [arXiv:1101.0862](https://arxiv.org/abs/1101.0862).
  - [22] See, e.g., A. B. Zorin and F. Chiarello, *Phys. Rev. B* **80**, 214535 (2009).